

# Power Limitation on Delta Solar Inverter SOLIVIA 5.0 TR

Applicable for Delta Solar Inverter SOLIVIA 5.0 AP G3 TR (software version 1v0b10) which were manufactured by:

## Delta Electronics (Thailand) Public Company Ltd.

909 Soi9 Moo4 Bangpoo Ind. Estate (E.P.Z.)  
Pattana 1 Rd., Tambol Phraksa Amphur Muang  
Samutprakarn 10280  
THAILAND



Dear Installer,

please note that **Power Limitation (PL)** is required in certain states in Australia.

- Therefore, we adjust the output (AC) power of your SOLIVIA 5.0 AP G3 TR as followed:
  - » Power limitation setting AU PL 4.60 -> Max. power: 4600 W
  - » Power limitation setting AU PL 4.99 -> Max. power: 4990 W
- To activate Power Limitation, please select dedicated country "Australia PL" (Installed settings are password protected):
  1. Select unit ID = [1] & press <ENTER> key
  2. Select country = [Australia PL] & press <ENTER> key
  3. Confirm country selection by pressing <ENTER> key
- When using the Power Limitation setting the label that is enclosed in the box of the inverter **MUST** be attached above/below to the model label:



For Australia PL4.60  
This product has been power limited  
at maximal output power of: 4.60 kW



For Australia PL4.99  
This product has been power limited  
at maximal output power of: 4.99 kW

- To check if Power Limitation has been activated, please go to the menu S (Setup) and press the „UP“ or „DOWN“ buttons to find the following display message:

Down ↓      Up ↑  
S -> Firmware AU PL 4.60

Down ↓      Up ↑  
S -> Firmware AU PL 4.99

- For further information, please download our latest manual of SOLIVIA 5.0 AP G3 TR through the following link: <http://www.solar-inverter.com/au>

## Delta Energy Systems (Australia) Pty. Ltd.

Unit 6, 25 Howleys Road  
Notting Hill VIC3168, Australia  
Service support: +61 3 9543 3053  
Support Email: [support.australia@solar-inverter.com](mailto:support.australia@solar-inverter.com)



5010701501 01

September 17<sup>th</sup> 2012

